

Telephone KX-TG6811

Features

Noise Reduction

Reduce the background noise of the other party

When the area around the other party is noisy and it is difficult to hear, you can reduce the surrounding noise to make the speaker's voice easier to hear just by pressing the dedicated button.

Smart Function Key

Easy access to necessary functions

The Smart Function Key flashes according to the situation. By pressing this key while it is flashing, you can respond to a call.

With the slow flashing NR key,

• View the caller list when there are missed calls if there was a call while you were away.

With the fast flashing NR key,

- Answer the call on speakerphone.
- Stop the alarm sound (then switches it to snooze mode).
- Enable Noise Reduction during a call.

Power Back-Up Operation

You can even use the phone during a power failure

During an electric power failure, you can supply the power stored in your handset to the base unit, so you can make calls for a certain period of time even when the power is out.

Key Finder Compatible

The handset detects lost items

Simply attach the Key Finder to items that you often misplace, and use the handset to find them quickly and easily. You can see roughly how close you are to your lost item on the LCD screen, and both the handset and Key Finder beep when being searched for, making them easy to find. You can add up to four Key Finders (sold separately).

* The optional Key Finder KX-TGA20 is required.

Key Finder Compatible

Smart Function Key

Specs

1.8-inch White Backlight LCD Noise Reduction Incoming Call Barring

Accessories



KX-TGA20EX

Optional Key Finder

Telephone KX-TG6811

General	Colour	B[Black]
	Handset (Quantity)	1
	Frequency	1.9 GHz
	Frequency Range	1.88 GHz - 1.90 GHz
	Number of Channels	120 Channels
	System	DECT
	GAP	Y
	Number of Phone Lines	1.0
	Multiple Handsets Capability	Up to 6 Handsets
	Multiple Base Units Capability	-
	LCD Language	English,
	LCD Language	Arabic,
	LCD Language	Persian
	Key Finder Compatible	Y
	Key Finder Compatible	* Please contact Panasonic or authorised sales department for availability of "key finder" in your area.
	Power Back-Up Operation	Y
	Power Back-Up Operation	* The built-in power unit supplies power to base unit to continue conversation in the case of a power outage.
	Power Back-Up Operation	After running out of power unit in base unit, the handset supplies temporary power to base unit.
	Baby Monitor	-
	Night Mode	Y
	Clear Sound	Y
	SMS	-
	Call Restriction	Y
	Distress Call	-
	Low Radio Power	Y
	One Touch Eco Mode	Y
	Repeater Available	Y
Link-to-Cell	Link-to-Cell	-
	Mobile Registration Number	-
	Ring as Cell Mode	-
	Text Message Alert	-
	USB Charging	-
Caller ID/	Caller ID	Y
Phonebook	Caller ID	* Requires subscription to Caller ID and / or

		SMS service offered by your telephone
		company.
	Caller ID Memory	50 items
	Caller ID Memory	* Requires subscription to Caller ID and / or
		SMS service offered by your telephone
		company.
	Call Waiting Caller ID	Y
	Call Waiting Caller ID	* Requires subscription to Caller ID and / or
		SMS service offered by your telephone
		company.
	Category Ringer / Ringer ID	-
	Category Display Colours	-
	Talking Caller ID (Handset)	-
	Talking Caller ID (Base Unit)	-
	Talking Caller ID Language	-
	Incoming Call Barring	Y(50 numbers)
	Incoming Call Barring	* Requires subscription to Caller ID and / or
		SMS service offered by your telephone
		company.
	Voice Mail	Y
	Voice Mail Alert (Light-Up	-
	Indicator on Handset)	
	Handset Phonebook Memory	100 items
	(Name/Number)	
	Handset Phonebook Memory	(16char/24digits)
	(Name/Number)	
	Base Unit Phonebook Memory	-
	(Name/Number)	
	Shared Phonebook	-
	Phonebook Copy (Handset to	Y
	Handset)	
	Phonebook Copy from	-
	Cellular Phone via Bluetooth	
	Speed Dial (Handset)	Y
	Speed Dial (Base Unit)	-
	Chain Dial	Y(Handset)
Handset	LCD	1.8 inch
	LCD	FullDot Monochrome
	LCD	103x65 pixels
	LCD Backlight Colour	White
	Illuminated Keypad	Amber
	Speakerphone (Volume Steps)	Y(6-step)
	Icon Operation (Number of	Y(6)
	Icons)	
	•	

	D' D' (T. M.1.1)	40/10 (20)
	Ringer Pattern (Tone+Melody)	40(10+30)
	Polyphonic Ringer Melody	32 chord
	Ringer Volume Steps	6+OFF
	Receiver Volume Steps	4.0
	Redial Memory	10(Name & Number)
	Redial Memory	* It requires registration in the phonebook to display the name.
	Digits of Redial Number	24.0
	Auto Redial	-
	Ringer/ Charger Indicator (Colour)	Y(Amber)
	Smart Function Key	Y
	Noise Reduction	Y
	Customized Sound System (Equalizer)	Treble/Bass
	Conference Call with Outside Line	-
	Call Share	-
	Intercom (Handset to Base	-
	Unit)	
	Intercom (Handset to Handset)	-
	Any Key Answer	Y
	Hold	Y
	Mute	Y
	Flash	Y
	Clock	Y
	Calendar/Scheduler	-
	Alarm (Wake-up / Memo alarm)	Y/Y
	Advanced Alarm (A day of the week / Snooze)	Y/Y
	Key Lock	Y
	Bluetooth Headset Capability	-
	Headset Jack	-
	Reversible Handset Charging	-
	Secure Grip	-
	Short Stroke Key	Y
	Wall Mountable (Charger)	-
Base Unit	Dial Keypad	-
	Corded Handset (Power	-
	Outage Operation)	
	Display	-
	Speakerphone (Volume Steps)	-
	Ringer Pattern (Tone+Melody)	-
	(<u> </u>

	Ringer Volume Steps	-
	Redial Memory	-
	Auto Redial	-
	Hold	-
	Mute	-
	Flash	-
	Handset Locator	Y
	Wall Mountable	-
Answering	Answering System	-
System	Total Recording Time	-
25222	Fast-Forwarding and	-
	Rewinding Message	
	Audible Message Alert	-
	Message Alert (Light-Up	-
	Indicator on Handset)	
	New Message Notification by	-
	a Call	
	Announcement Language of	-
	New Message Notification	
	New Message Notification by	-
	an SMS	
	Visual Message List (Handset	-
	LCD)	
	Recording Conversation	-
	Speaker Volume (Base Unit	-
	Speaker)	
	Call screening (Handset)	-
	Call screening (Base Unit)	-
	Language of Pre-recorded	-
	Greeting Message	
	Remote Operation from	-
	Handset	
	Remote Operation from	-
	Outside (DTMF)	
	Toll Saver (New Messages	-
Accessories	Recorded / No New Message) Key Finder Included	
Accessories	(Quantity)	-
	Repeater Included	-
	Belt Clip Included	_
Optional	Optional Handset	-
Handset	Rechargeable Battery	Ni-MH(AAA x 2)
Handset	Talk Time	Up to 15 hours
	Standby Time	Up to 170 hours
	Standby Time	Op to 170 hours

	Charge Time	About 7 hours
Power	Standby Power Consumption	0.6 W
Consumption		
Dimensions/	Base Dimensions (W x D x H)	$107 \text{ mm} \times 86 \text{ mm} \times 77 \text{ mm}$
Weight	Handset Dimensions (W x D x H)	$48 \text{ mm} \times 29 \text{ mm} \times 164 \text{ mm}$
	Charger Dimensions (W x D x H)	$70 \text{ mm} \times 70 \text{ mm} \times 39 \text{ mm}$
	Key Finder Dimensions (W x D x H)	-
	Repeater Dimensions (W x D x H)	-
	Base Weight	Approx. 98 g
	Handset Weight with Battery	Approx. 129 g
	Charger Weight	Approx. 39 g
	Key Finder Weight	-
	Repeater Weight	-

