



Cordless Phone KX-TGF352

Features

- EASY-TO-USE
- EASY-TO-HEAR
- CONVENIENCE

Tilt LCD Display / One-touch Dial Buttons

Designed for easy use with a large 3.4 inch LED that can be adjusted for maximum ease of both use and viewing.

The three one-touch dial buttons allow phone calls to be made more easily.

Specs



Cordless Phone KX-TGF352

| General | Colour | M [Metallic Black] |
|---------------------------|---------------------------------|---------------------|
| | Handset (Quantity) | 2 |
| | Frequency | 1.9 GHz |
| | Frequency Range | 1.92 GHz - 1.93 GHz |
| | Number of Channels | 60 Channels |
| | System | DECT6.0 |
| | Number of Phone Lines | 1 |
| | Multiple Handsets Capability | Up to 6 Handsets |
| | Multiple Base Units Capability | - |
| | LCD Language | English, French |
| | Wi-Fi® Connection | - |
| | Bluetooth® Class | - |
| | Android™ OS Version | - |
| Power Saving | Intelligent ECO Mode | Y |
| Smartphone Connect | Smartphone Connect | - |
| | Multiple Smartphones Capability | - |
| | Supported Devices | - |
| | Wireless Network Standard | - |
| | Simplified Configuration | - |
| | Easy Wi-Fi Setup Button | - |

| | | |
|-----------------------------------|--|---|
| | Wi-Fi Repeater Mode | - |
| | Phonebook Copy from Smartphone | - |
| | Ringtone Copy from Smartphone | - |
| | Wallpaper Image Copy from Smartphone | - |
| | Conference Call with Outside Landline and Smartphone | - |
| | Transferring Landline Call (between Smartphone and Handsets) | - |
| | Playing Answering System Messages | - |
| Link-to-Cell | Link-to-Cell | - |
| | Mobile Registration Number | - |
| | Mobile Registration by Easy Setup | - |
| | Simultaneous Communication | - |
| | Ring as Cell Mode | - |
| | Text Message Alert | - |
| | Talking Text Sender Alert | - |
| | Application Alert | - |
| Smartphone Docking Station | Device Battery Charging | - |
| | Smartphone Stand | - |
| | Stereo Speaker | - |
| | Compatible Devices of Battery Charging | - |
| | Playing Music from a Bluetooth® Device | - |
| Convenience | Music Player Remote Control by DECT Handset | - |
| | Key Detector Compatible | Y |
| | Multiple Key Detector Capability | Up to 4 Key Detector |
| | Range Extender Available | Y |
| | Range Boost | Y |
| | Noise Reduction | Y |
| | Noise Reduction (Answering System) | Y * When using the base unit or handset to listen to messages, the noise reduction feature is activated automatically. |
| | Customized Sound System (Equalizer) | Treble/Bass |
| Compatible with Hearing Aid T- | Y | |

| | | |
|--|--|--|
| Coil (TIA-1083 Compliant) | | |
| Power Back-Up Operation | Y * The base unit gets temporary power supply from 2 rechargeable batteries in the case of a power outage. | |
| Baby Monitor | Y | |
| Smart Function Key | - | |
| Any Key Answer | Y | |
| Night Mode | Y | |
| Bypassing Night Mode (Specified Phonebook Group) | Y * Requires subscription to Caller ID service offered by your provider/telephone company. | |
| Voice Mail | Y * Requires subscription to a Voice Mail service offered by your provider/telephone company. | |
| Voice Mail Alert (Light-Up Indicator on Handset) | - | |
| Conference Call with Outside Line | Y 3Way * Optional handset may be required depending on the model. ** 3Way: Base unit - Handset - Landline or Handset - Handset - Landline | |
| Barge In (Call Share) | Y | |
| Intercom (Handset to Base Unit) | Y | |
| Intercom (Handset to Handset) | Y | |
| Intercom All | Y (Base/Handset) | |
| Clock | Y | |
| Calendar/Scheduler | - | |
| Alarm (Wake-up / Memo alarm) | Y/Y | |
| Advanced Alarm (A day of the week / Snooze) | Y/Y | |
| Bluetooth® Headset Capability (HSP Support) | - | |
| Bluetooth® Audio Headphone/Speaker Capability (A2DP Support) | - | |
| Google Play™ Support | - | |
| Call from Outlook (Telephone Plug-in) | - | |
| Caller ID / Phonebook | Caller ID | Y * Requires subscription to a Caller ID service offered by your provider/telephone company. |
| | Caller ID Memory | 50 items * Requires subscription to a Caller ID service offered by your provider/telephone company. |
| | Call Waiting Caller ID | Y |

| | | |
|----------------|---|---|
| | | * Requires subscription to a Caller ID and Call Waiting service offered by your provider/telephone company. |
| | Category Ringer / Ringer ID | Y * Requires subscription to a Caller ID service offered by your provider/telephone company. ** Requires registration in Phonebook function. |
| | Talking Caller ID (Handset) | Y * Requires subscription to a Caller ID service offered by your provider/telephone company. ** Name pronunciation may vary. |
| | Talking Caller ID (Base Unit) | Y * Requires subscription to a Caller ID service offered by your provider/telephone company. ** Name pronunciation may vary. |
| | Talking Caller ID Language | English, French * Requires subscription to a Caller ID service offered by your provider/telephone company. ** Name pronunciation may vary. |
| | Call Block | Y(250 numbers) * Requires subscription to a Caller ID service offered by your provider/telephone company. ** Requires number registration in the call block list. |
| | Call Block Registration using Call Block button (Handset) | Y |
| | Call Block Registration using Call Block button (Base Unit) | Y |
| | Handset Phonebook Memory (Name/Number) | - |
| | Base Unit Phonebook Memory (Name/Number) | 100 items (16 char / 24 digits) |
| | Phonebook Copy from Cellular Phone via Bluetooth® | - |
| | One-Touch Dial (Base Unit) | Y (3 buttons) |
| | Speed Dial (Handset) | Y |
| | Speed Dial (Base Unit) | Y |
| | Chain Dial (Handset) | Y |
| | Chain Dial (Base Unit) | Y |
| Handset | LCD | 1.8 inch Full Dot Monochrome 103 x 65 pixels |
| | LCD Backlight Colour | White |
| | Touchscreen | - |
| | Front Camera | - |
| | Rear Camera | - |
| | LED Flash | - |
| | GPS | - |

| | | | |
|-------------------------|------------------------------|---|--------------|
| | SD Memory Card Slot | - | |
| | USB Jack | - | |
| | USB Version | - | |
| | Lighted Handset Keypad | Amber | |
| | Speakerphone (Volume Steps) | Y (7-step) | |
| | Full Duplex Speakerphone | Y | |
| | Ringer Pattern (Tone+Melody) | 15 (5+10) | |
| | Ringer Volume Steps | 6+OFF | |
| | Receiver Volume Steps | 5.0 | |
| | Redial Memory | 5 (Name & Number) * Requires registration in the phonebook to display the name. | |
| | Ringer Indicator (Colour) | - | |
| | Charge Indication (Colour) | - | |
| | Hold | Y | |
| | Music on Hold | - | |
| | Mute | Y | |
| | Flash | Y | |
| | Headset Jack | Y | |
| | Reversible Handset Charging | - | |
| | Rubber Grip | - | |
| | Wall Mountable (Charger) | Y | |
| Base Unit | Dial Keypad | Y | |
| | Corded Handset | Y | |
| | Display | 3.4 inch mono 103 x 65 pixels 3 Line+Softkey or 2Line+Pict+Softkey | |
| | Speakerphone (Volume Steps) | Y (8-step) | |
| | Ringer Pattern (Tone+Melody) | 1 (1+0) | |
| | Ringer Volume Steps | 6+OFF | |
| | Redial Memory | 10 (Name & Number) * Requires registration in the phonebook to display the name. | |
| | Locates Cell | - | |
| | Hold | Y | |
| | Music on Hold | - | |
| | Mute | Y | |
| | Flash | Y | |
| | Handset Locator | Y | |
| | Headset Jack | - | |
| | Wall Mountable | Y | |
| | Answering System | Answering System | Y |
| | | Total Recording Time | About 15 min |
| 2-Line Answering System | | - | |

| | | |
|----------------------------|---|---|
| | Operation | |
| | Optional greeting message for each line | - |
| | Programmable greeting message by time setting | - |
| | Fast-Forwarding and Rewinding Message | - |
| | Audible Message Alert | Y (Base Unit) |
| | Message Alert (Light-Up Indicator on Handset) | - |
| | New Message Notification by a Call | Y |
| | Announcement Language of New Message Notification | English, French |
| | Visual Message List (Handset LCD) | - |
| | Recording Conversation | - |
| | Speaker Volume Steps(Base Unit Speaker) | 8.0 |
| | Call Screening (Handset) | Y |
| | Call screening (Base Unit) | Y |
| | Language of Pre-recorded Greeting Message | English, French |
| | Remote Operation from Handset | Y |
| | Remote Operation from Outside (DTMF) | Y |
| | Toll Saver (New Messages Recorded / No New Message) | 2/5 |
| Accessories | Key Detector Included (Quantity) | - |
| | Range Extender Included | - |
| | Belt Clip Included | Y |
| Optional Handset | Optional Handset | KX-TGFA30 |
| Others | Rechargeable Battery | Base Unit: Ni-MH (AAA x 2) Handsett: Ni-MH (AAA x 2) |
| | Talk Time | 13 hours |
| | Standby Time | 12 days |
| | Charge Time | 7 hours |
| Power Consumption | Base Unit Standby Power Consumption | 0.7W |
| | Charger Standby Power Consumption | 0.1W |
| Dimensions / Weight | Base Unit Dimensions (W x D x H) | Approx. 222 x 163 x 103 mm |

| | |
|-------------------------------------|--------------------------|
| Handset Dimensions (W x D x H) | Approx. 48 x 30 x 168 mm |
| Charger Dimensions (W x D x H) | Approx. 72 x 73 x 39 mm |
| Key Detector Dimensions (W x D x H) | - |
| Repeater Dimensions (W x D x H) | - |
| Base Unit Weight | Approx. 580 g |
| Handset Weight with Battery | Approx. 140 g |
| Charger Weight | Approx. 100 g |
| Key Detector Weight | - |
| Range Extender Weight | - |